



RS2G125 Dual Bus Buffer Gate With 3-State Outputs

1 FEATURES

- Operating Voltage Range: 1.65V to 5.5V
- Low Power Consumption:1µA (Max)
- Operating Temperature Range: -40°C to +125°C
- Inputs Accept Voltage to 5.5V
- ±24mA Output Drive at Vcc=3.0V
- ESD Protection Exceeds JESD 22
 - 4000-V Human-Body Model (A114)
 - 200-V Machine Model (A115)
 - 1000-V Charged-Device Model (JS-002)
- Latch-up Performance Exceeds 100mA
- PACKAGE: MSOP-8

2 APPLICATIONS

- AV Receiver
- Cable Modem Termination Systems
- Digital Picture Frame (DPF)
- High-Speed Data Acquisition and Generation
- Motor Controls: High-Voltage
- Personal Navigation Device (GPS)
- Portable Media Player
- Video Communication Systems



3 DESCRIPTIONS

The dual buffer is designed for 1.65V to 5.5V V_{CC} operation. The RS2G125 device is dual line drivers with 3-state outputs. The outputs are disabled when the output-enable ($\overline{\text{OE}}$) input is high.

This device is fully specified for partial-power-down applications using loff. The loff circuitry disables the outputs, preventing damaging current backflow through the device when it is powered down.

To ensure the high-impedance state during power up or power down, \overline{OE} should be tied to V_{CC} through a pullup resistor, the minimum value of the resistor is determined by the current-sinking capability of the driver.

The RS2G125 is available in Green MSOP-8 package. It operates over an ambient temperature range of - 40° C to +125°C.

Device Information⁽¹⁾

PART NUMBER	PACKAGE	BODY SIZE (NOM)	
RS2G125	MSOP-8	3.00mm×3.00mm	

(1) For all available packages, see the orderable addendum at the end of the data sheet.

4 FUNCTION TABLE

INP	UTS	OUTPUT
ŌĒ	А	Y
L	Н	Н
L	L	L
Н	Х	Z

H=HIGH Logic Level L =LOW Logic Level X=Don't Care Z=High-impedance OFF-state



Table of Contents

1 FEATURES	1
2 APPLICATIONS	1
3 DESCRIPTIONS	
4 FUNCTION TABLE	
5 Revision History	3
6 PACKAGE/ORDERING INFORMATION ⁽¹⁾	4
7 PIN CONFIGURATIONS	5
8 Specifications	
8.1 Absolute Maximum Ratings ⁽¹⁾	6
8.2 ESD Ratings	6
9 ELECTRICAL CHARACTERISTICS	
9.1 Recommended Operating Conditions	
9.2 Electrical Characteristics	
9.3 Switching Characteristics, CL=15pF	
9.4 Switching Characteristics, CL=30pF or 50pF	
9.5 Operating Characteristics	
10 Parameter Measurement Information	
11 PACKAGE OUTLINE DIMENSIONS	11
12 TAPE AND REEL INFORMATION	12



5 Revision History <u>Note: Page numbers for previous revisions may different from page numbers in the current version.</u>

Version	Change Date	Change Item
A.1	2021/02/05	Initial version completed
A.2	2021/12/22	Added the TAPE AND REEL INFORMATION
A.3	2022/09/01	1. Change TSSOP8 package to MSOP8 package 2. Change ORDERING NUMBER
A.4	2024/01/12	 Update FEATURES on Page 1@RevA.3 Add MSL on Page 4@RevA.3 Update Package thermal impedance and ESD Ratings on Page 6@RevA.3



6 PACKAGE/ORDERING INFORMATION⁽¹⁾

PRODUCT	ORDERING NUMBER	TEMPERATURE RANGE	PACKAGE LEAD	PACKAGE MARKING ⁽²⁾	MSL ⁽³⁾	PACKAGE OPTION
RS2G125	RS2G125XM	-40°C ~+125°C	MSOP-8	RS2G125	MSL3	Tape and Reel,4000

NOTE:

(1) This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the right-hand navigation.

(2) There may be additional marking, which relates to the lot trace code information (data code and vendor code), the logo or the environmental category on the device.

(3) MSL, The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications.



7 PIN CONFIGURATIONS



PIN DESCRIPTION

PIN		I/O TYPE ⁽¹⁾	FUNCTION			
MSOP-8	NAME		FUNCTION			
1	$1\overline{OE}$	I	Output Enable for buffer 1			
2	1A	I	Input of buffer 1			
3	2Y	0	Output of buffer 2			
4	GND	-	Ground			
5	2A	I	Input of buffer 2			
6	1Y	0	Output of buffer 1			
7	$2\overline{OE}$	I	Output Enable for buffer 2			
8	V _{cc}	-	Power Pin			

(1) I=input, O=output.



8 Specifications

8.1 Absolute Maximum Ratings⁽¹⁾

over operating free-air temperature range (unless otherwise noted)⁽¹⁾⁽²⁾

			MIN	MAX	UNIT
Vcc	Supply voltage range		-0.5	6.5	V
VI	Input voltage range ⁽²⁾		-0.5	6.5	V
Vo	Voltage range applied to any output in the high-impedan	ice or power-off state ⁽²⁾	-0.5	6.5	V
Vo	Voltage range applied to any output in the high or low sta	-0.5	Vcc+0.5	V	
Ік	Input clamp current	V _I <0		-50	mA
Іок	Output clamp current	V ₀ <0		-50	mA
lo	Continuous output current			±50	mA
	Continuous current through V_{CC} or GND			±100	mA
ALθ	Package thermal impedance ⁽⁴⁾	MSOP-8		199	°C/W
٦J	Junction temperature ⁽⁵⁾			150	°C
T _{stg}	Storage temperature		-65	150	°C

(1) Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under Recommended Operating Conditions is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

(2) The input and output negative-voltage ratings may be exceeded if the input and output current ratings are observed.

(3) The value of V_{cc} is provided in the Recommended Operating Conditions table.

(4) The package thermal impedance is calculated in accordance with JESD-51.

(5) The maximum power dissipation is a function of $T_{J(MAX)}$, $R_{\theta JA}$, and T_A . The maximum allowable power dissipation at any ambient temperature is $P_D = (T_{J(MAX)} - T_A) / R_{\theta JA}$. All numbers apply for packages soldered directly onto a PCB.

8.2 ESD Ratings

The following ESD information is provided for handling of ESD-sensitive devices in an ESD protected area only.

		VALUE	UNIT
	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001 ⁽¹⁾	±4000	V
V _(ESD) Electrostatic discharge	Charged-device model (CDM)	±1000	V
	Machine model (MM)	±200	V

(1) JEDEC document JEP155 states that 500 V HBM allows safe manufacturing with a standard ESD control process.



ESD SENSITIVITY CAUTION

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.



9 ELECTRICAL CHARACTERISTICS

over recommended operating free-air temperature range (TYP values are at T_A = +25°C, unless otherwise noted.)⁽¹⁾

9.1 Recommended Operating Conditions

PARAMETER	SYMBOL	TEST CONDITIONS	MIN	MAX	UNIT	
Current under aus	M	Operating	1.65	5.5	- v	
Supply voltage	Vcc	Data retention only	1.5	5.5	v	
		V _{CC} =1.65V to 1.95V	0.65xVcc			
1 link land in materia kana	N/	V _{CC} =2.3V to 2.7V	1.7		- V	
Hign-level input voltage	VIH	V _{CC} =3V to 3.6V	2.2		v	
		V _{CC} =4.5V to 5.5V	V 2.2 .5V 0.7xVcc 1.95V 0.15xVcc .7V 0.3			
Output voltage	VIL	V _{CC} =1.65V to 1.95V		0.15xVcc		
		V _{CC} =2.3V to 2.7V		0.3		
		V _{CC} =3V to 3.6V		0.4		
		V _{CC} =4.5V to 5.5V		0.15xVcc		
Input voltage	VI		0	5.5	V	
Output voltage	Vo		0	Vcc	V	
		V _{CC} =1.8V± 0.15V, 2.5V ± 0.2V		20		
Input transition rise or fall	tr, t _f	V _{CC} =3.3V± 0.3V		10	ns/V	
		V _{CC} =5V± 0.5V		5		
Operating temperature	TA		-40	+125	°C	

(1) All unused inputs of the device must be held at V_{CC} or GND to ensure proper device operation.



9.2 Electrical Characteristics

PA	ARAMETER	TEST CONDITIONS	Vcc	TEMP	MIN ⁽²⁾	TYP ⁽³⁾	MAX (2)	UNIT	
		Іон = -100μА	1.65V to 5.5V		Vcc-0.1				
$\begin{tabular}{ c c c c c c } \hline V_{OH} & $I_{0H} = -100\mu A$ & $1.65V$ to $5.5V$ \\ \hline $I_{0H} = -4m A$ & $1.65V$ to $5.5V$ \\ \hline $I_{0H} = -8m A$ & $2.3V$ \\ \hline $I_{0H} = -16m A$ & $2.3V$ \\ \hline $I_{0H} = -24m A$ & $3V$ \\ \hline $I_{0H} = -32m A$ & $4.5V$ & 3.8 \\ \hline $I_{0L} = 100\mu A$ & $1.65V$ to $5.5V$ \\ \hline $I_{0L} = 4m A$ & $1.65V$ to $5.5V$ \\ \hline $I_{0L} = 4m A$ & $1.65V$ to $5.5V$ \\ \hline $I_{0L} = 4m A$ & $1.65V$ to $5.5V$ \\ \hline $I_{0L} = 4m A$ & $1.65V$ to $5.5V$ \\ \hline $I_{0L} = 8m A$ & $2.3V$ \\ \hline $I_{0L} = 16m A$ & $3V$ \\ \hline $I_{0L} = 16m A$ & $3V$ \\ \hline $I_{0L} = 24m A$ & $3V$ \\ \hline $I_{0L} = 32m A$ & $4.5V$ & $Full$ \\ \hline $I_{0L} = 32m A$ & $4.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ & $1.65V$ to $5.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ & $1.65V$ to $5.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ & $1.65V$ to $5.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ & $1.65V$ to $5.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ & $1.65V$ to $5.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ & $1.65V$ to $5.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ & $1.65V$ to $5.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ & $1.65V$ to $5.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ & $1.65V$ to $5.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ & $1.65V$ to $5.5V$ & 10 \\ \hline $I_{0L} = 1000 P$ $									
		V							
	∨он	Iон = -16mA	2)/	Full	2.4			v	
	$ \begin{array}{c c c c c c c c c c c c c c c c c c c $								
		I _{он} = -32mA	$\begin{array}{c c c c c c c c c c c c c c c c c c c $						
		I _{OL} = 100μA	1.65V to 5.5V				0.1		
	V _{OL}	I _{OL} = 4mA	1.65V				0.45	V	
		I _{OL} = 8mA	2.3V	F			0.3		
		I _{OL} = 16mA	3V	Full			0.4		
		I _{OL} = 24mA					0.55		
		I _{OL} = 32mA	4.5V				0.55		
	A or \overline{OE}			+25°C		±0.1	±1		
11	inputs	VI=5.5V or GND	UV to 5.5V	Full			±5	μΑ	
			0) (+25°C		±0.1	±1	•	
	loff	VIOr V0=5.5V	00	Full			±10	μΑ	
	loz	V ₀ =0V to 5.5V	3.6V	Full			10	μA	
	1			+25°C		0.1	1		
	ICC	VI=3.3V OF GIND, IO=U	1.03 V to 5.5 V	Full			10	μΑ	
				Full			500	μA	

 All unused inputs of the device must be held at V_{cc} or GND to ensure proper device operation.
 Limits are 100% production tested at 25°C. Limits over the operating temperature range are ensured through correlations using statistical quality control (SQC) method.

(3) Typical values represent the most likely parametric norm as determined at the time of characterization. Actual typical values may vary over time and will also depend on the application and configuration.



9.3 Switching Characteristics, CL=15pF

over recommended operating free-air temperature range (-40°C to 125°C, unless otherwise noted.)⁽¹⁾

	FROM	то	Vcc=1.8V±0.15V	Vcc=2.5V±0.2V	Vcc=3.3V±0.3V	Vcc=5V±0.5V	UNIT
PARAMETER	(INPUT) (OUTPUT)	ТҮР	ТҮР	ТҮР	ТҮР	UNIT	
t _{pd}	А	Y	6.1	3.7	3.9	2.1	ns

(1) All unused inputs of the device must be held at V_{CC} or GND to ensure proper device operation.

9.4 Switching Characteristics, CL=30pF or 50pF

over recommended operating free-air temperature range (-40°C to 125°C, unless otherwise noted.)⁽¹⁾

PARAMETER FROM		то	Vcc=1.8V±0.15V	Vcc=2.5V±0.2V	Vcc=3.3V±0.3V	Vcc=5V±0.5V	UNIT
PARAMETER	(INPUT)	(OUTPUT)	ТҮР	ТҮР	ТҮР	ТҮР	UNIT
t _{pd}	А	Y	8.6	5.3	4.0	2.9	ns
t _{en}	ŌĒ	Y	9.5	5.8	5.0	3.3	ns
t_{dis}	ŌĒ	Y	7.4	4.3	4.4	3.0	ns

(1) All unused inputs of the device must be held at V_{CC} or GND to ensure proper device operation.

9.5 Operating Characteristics

T_A=25°C

PARAMETER		TEST	Vcc=1.8V	Vcc=2.5V	Vcc=3.3V	Vcc=5V	UNIT	
	PARAMEI	ER	CONDITIONS	ТҮР	TYP TYP TYP			
C .	Power dissipation	Output enabled	£-10MU-	18	18	19	21	~ Г
Cpd	capacitance	Output disabled	f=10MHz	2	2	2	4	рF



10 Parameter Measurement Information

From Outp <u>ut</u> Under Test	RL O Open

O VLOAD

TEST	S1
tplh/tphl	Open
tplz/tpzl	VLOAD
tphz/tpzh	GND

Ver	INPUTS		V _M	V	Ċ	RL	V.	
Vcc	Vı	t _r /t _f	₩М	VLOAD	C∟	ĸL	VΔ	
1.8V±0.15V	Vcc	≤2ns	Vcc/2	2 x Vcc	15pF	1ΜΩ	0.15V	
2.5V±0.2V	Vcc	≤2ns	Vcc/2	2 x Vcc	15pF	1ΜΩ	0.15V	
3.3V±0.3V	3V	≤2.5ns	1.5V	6V	15pF	1MΩ	0.3V	
5V±0.5V	Vcc	≤2.5ns	V _{cc} /2	$2 \times V_{CC}$	15pF	1ΜΩ	0.3V	



VOLTAGE WAVEFORMS PROPAGATION DELAY TIMES INVERTION AND NONINVERTING OUTPUTS

NOTES: A. C_L includes probe and jig capacitance.

B. Waveform 1 is for an output with internal conditions such that the output is low, except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high, except when disabled by the output control.

LOW-AND HIGH-LEVEL ENABLING

C. All input pulses are supplied by generators having the following characteristics: PRR \leq 10 MHz, Z₀ = 50 Ω .

- D. The outputs are measured one at a time, with one transition per measurement.
- E. t_{PLZ} and t_{PHZ} are the same as t_{dis} .
- F. t_{PZL} and t_{PZH} are the same as t_{en} .
- G. t_{PLH} and t_{PHL} are the same as t_{pd} .
- H. All parameters and waveforms are not applicable to all devices.

Figure 1. Load Circuit and Voltage Waveforms



11 PACKAGE OUTLINE DIMENSIONS

MSOP-8⁽³⁾





RECOMMENDED LAND PATTERN (Unit: mm)





Symbol	Dimensions I	n Millimeters	Dimensions In Inches			
Symbol	Min Max		Min	Max		
A ⁽¹⁾	0.820	1.100	0.032	0.043		
A1	0.020	0.150	0.001	0.006		
A2	0.750	0.950	0.030	0.037		
b	0.250	0.380	0.010	0.015		
С	0.090	0.230	0.230 0.004 3.100 0.114			
D ⁽¹⁾	2.900	3.100				
e	0.650(BSC) ⁽²⁾	0.026(BSC) ⁽²⁾			
E ⁽¹⁾	2.900	3.100	0.114	0.122		
E1	4.750	5.050	0.187	0.199		
L	0.400	0.800	0.016	0.031		
θ	0°	6°	0°	6°		

NOTE:

1. Plastic or metal protrusions of 0.15mm maximum per side are not included.
2. BSC (Basic Spacing between Centers), "Basic" spacing is nominal.
3. This drawing is subject to change without notice.



12 TAPE AND REEL INFORMATION REEL DIMENSIONS

TAPE DIMENSION



NOTE: The picture is only for reference. Please make the object as the standard.

KEY PARAMETER LIST OF TAPE AND REEL

Package Type	Reel	Reel	A0	B0	K0	P0	P1	P2	W	Pin1
	Diameter	Width(mm)	(mm)	Quadrant						
MSOP-8	13"	12.4	5.20	3.30	1.50	4.0	8.0	2.0	12.0	Q1

NOTE:

1. All dimensions are nominal.

2. Plastic or metal protrusions of 0.15mm maximum per side are not included.



IMPORTANT NOTICE AND DISCLAIMER

Jiangsu RUNIC Technology Co., Ltd. will accurately and reliably provide technical and reliability data (including data sheets), design resources (including reference designs), application or other design advice, WEB tools, safety information and other resources, without warranty of any defect, and will not make any express or implied warranty, including but not limited to the warranty of merchantability Implied warranty that it is suitable for a specific purpose or does not infringe the intellectual property rights of any third party.

These resources are intended for skilled developers designing with RUNIC products You will be solely responsible for: (1) Selecting the appropriate products for your application; (2) Designing, validating and testing your application; (3) Ensuring your application meets applicable standards and any other safety, security or other requirements; (4) RUNIC and the RUNIC logo are registered trademarks of RUNIC INCORPORATED. All trademarks are the property of their respective owners; (5) For change details, review the revision history included in any revised document. The resources are subject to change without notice. Our company will not be liable for the use of this product and the infringement of patents or third-party intellectual property rights due to its use.